

rom PTO-1390
P21950.P01

U.S. DEPARTMENT OF COMMERCE
PATENT AND TRADEMARK OFFICE

ATTORNEY'S DOCKET NUMBER

P21950

TRANSMITTAL LETTER TO THE UNITED STATES
DESIGNATED/ELECTED OFFICE (DO/EO/US)
CONCERNING A FILING UNDER 35 U.S.C. 371

1. STANDARDIZATION. (If known, see 37 CFR 1.5)

INTERNATIONAL APPLICATION NO.

PCT/KR00/00856

INTERNATIONAL FILING DATE

03 August 2000

PRIORITY DATE CLAIMED

05 August 1999

TITLE OF INVENTION

METHOD AND APPARATUS FOR ORTHOGONAL CODE HOPPING MULTIPLEXING COMMUNICATIONS

APPLICANT(S) FOR DO/EO/US

Dan-Keun SUNG and Su Won PARK


Applicant herewith submits to the United States Designated/Elected Office (DO/EO/US) the following items and other information.

1. ☒ This is a FIRST submission of items concerning a filing under 35 U.S.C. 371.
2. ☐ This is a SECOND or SUBSEQUENT submission of items concerning a filing under 35 U.S.C. 371.
3. ☒ This is an express request to promptly begin national examination procedures (35 U.S.C. 371(f)).
4. ☒ The US has been elected by the expiration of 19 months from the priority date (PCT Article 31).
5. ☒ A copy of the International Application as filed (35 U.S.C. 371(c)(2))
- a. ☒ is attached hereto (required only if not communicated by the International Bureau).
- b. ☐ has been communicated by the International Bureau.
- c. ☐ is not required, as the application was filed in the United States Receiving Office (RO/US).
6. ☐ An English language translation of the International Application as filed (35 U.S.C. 371 (c)(2)).
7. ☐ Amendments to the claims of the International Application under PCT Article 19 (35 U.S.C. 371(c)(3))
- a. ☐ are attached hereto (required only if not communicated by the International Bureau).
- b. ☐ have been communicated by the International Bureau.
- c. ☐ have not been made; however, the time limit for making such amendments has NOT expired.
- d. ☐ have not been made and will not be made.
8. ☐ An English language translation of the amendments to the claims under PCT Article 19 (35 U.S.C. 371(c)(3))
9. ☒ An oath or declaration of the inventor(s) (35 U.S.C. 371(c)(4)).
10. ☐ An English language translation of the annexes to the International Preliminary Examination Report under PCT Article 36 (U.S.C. 371(c)(5)).

Items 11 to 16 below concern other document(s) or information included:

Assignee(s): KOREA ADVANCED INSTITUTE OF SCIENCE AND TECHNOLOGY of Taejeon, REPUBLIC OF KOREA and ELECTRONICS AND TELECOMMUNICATIONS RESEARCH INSTITUTE of Daejeon, REPUBLIC OF KOREA.

12. ☒ An Information Disclosure Statement under 37 CFR 1.97 and 1.98.
13. ☒ An assignment document for recording. A separate cover sheet in compliance with 37 CFR 3.28 and 3.31 is included.
14. ☒ A FIRST preliminary amendment.
15. ☐ A SECOND or SUBSEQUENT preliminary amendment.
15. ☐ A substitute specification.
16. ☐ A change of power of attorney and/or address letter.
17. ☒ Figure of Drawing to be published 2a
18. ☒ Other items or information:
Cover Sheet and International Application as published.
PCT/RO/101-PCT Request.
PCT/IB/304.
PCT/IPEA/402.
PCT/ISA/210.
Claim of Priority.

U.S. APPLICATION NO. (If known, see 37 CFR 1.5)		INTERNATIONAL APPLICATION NO.		ATTORNEY'S DOCKET NUMBER	
10/030190		PCT/KR00/00856		P21950	
19 <input checked="" type="checkbox"/> The following fees are submitted: Basic National Fee (37 CFR 1.492(a)(1)-(5)): Search report has been prepared by the EPO or JPO. \$ 890.00 International preliminary examination fee paid to USPTO (37 CFR 1.482)..... \$ 710.00 No international preliminary examination fee paid to USPTO (37 CFR 1.482) but international search fee paid to USPTO(37 CFR 1.445(a)(2)). \$ 740.00 Neither international preliminary examination fee (37 CFR 1.482) nor international search fee (37 CFR 1.445(a)(2)) paid to USPTO..... \$1,040.00 International preliminary examination fee paid to USPTO (37 CFR 1.482) and all claims satisfied provisions of PCT Article 33(2)-(4)..... \$ 100.00 ENTER APPROPRIATE BASIC FEE AMOUNT =				CALCULATIONS	PTO USE ONLY
				\$1040.00	
Surcharge of \$130.00 for furnishing the oath or declaration later than ____ 20 ____ 30 months from the earliest claimed priority date (37 CFR 1.492(e)).				\$	
Claims	Number Filed	Number Extra	RATE		
Total Claims	44 - 20 =	24	X \$18.00	\$432.00	
Independent Claims	3 - 3 =	0	X \$84.00	\$	
Multiple dependent claim(s) (if applicable)			+ \$280.00	\$	
TOTAL OF ABOVE CALCULATIONS =				\$1472.00	
<input checked="" type="checkbox"/> Applicant claims small entity status. See 37 CFR 1.27. The fees indicated above are reduced by 1/2.				\$736.00	
SUBTOTAL =				\$736.00	
Processing fee of \$130.00 for furnishing the English translation later than ____ 20 ____ 30 months from the earliest claimed priority date (37 CFR 1.492(f)).				+	
Extension of Time fee in the amount of \$					
TOTAL NATIONAL FEE =				\$736.00	
Fee for recording the enclosed assignment (37 CFR 1.21(h). The assignment must be accompanied by an appropriate cover sheet (37 CFR 3.28, 3.31). \$40.00 per property				+	\$40.00
TOTAL FEES ENCLOSED =				\$776.00	
				Amount to be refunded	\$
				Charged	\$
a. <input checked="" type="checkbox"/> A check in the amount of \$776.00 to cover the above fees is enclosed. b. ____ Please charge my Deposit Account No. ____ in the amount of \$ ____ to cover the above fees. c. <input checked="" type="checkbox"/> The Commissioner is hereby authorized to charge any additional fees which may be required, or credit any overpayment to Deposit Account No. 19-0089. NOTE: Where an appropriate time limit under 37 CFR 1.494 or 1.495 has not been met, a petition to revive (37 CFR 1.137(a) or (b)) must be filed and granted to restore the application to pending status. SEND ALL CORRESPONDENCE TO CUSTOMER NO. 7055 AT THE PRESENT ADDRESS OF: Bruce H. Bernstein GREENBLUM & BERNSTEIN, P.L.C. 1941 Roland Clarke Place Reston, VA 20191 (703) 716-1191					
			 07055 PATENT TRADEMARK OFFICE	Leslie Meyerman Reg. No. SIGNATURE Bruce H. Bernstein 33,329 NAME 29.027 REGISTRATION NUMBER	

P21950.A01

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicant : Dan-Keun SUNG et al.

Serial No : Not Yet Assigned (National Stage of PCT/KR00/00856)

Filed : Concurrently Herewith (International Filing Date August 3, 2000)

For : METHOD AND APPARATUS FOR ORTHOGONAL CODE HOPPING
MULTIPLEXING COMMUNICATIONS

PRELIMINARY AMENDMENT

Commissioner of Patents and Trademarks
Washington, D.C. 20231

Sir:

Prior to calculation of the filing fees and the examination of the above-identified patent application on the merits, the Examiner is respectfully requested to amend the claims as follows:

IN THE CLAIMS

Please amend the claims as follows (a marked-up copy of the claim amendments is provided as an attachment to this Amendment):

5. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 1,

wherein the orthogonal code is a Hadamard code.

P21950.A01

6. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 1,

wherein the orthogonal code is a variable spreading factor code.

7. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 1,

wherein the orthogonal code is a gold code.

8. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 3, further comprising the step of:

allocating the orthogonal code hopping pattern to the second communication stations dedicatedly.

9. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 3,

wherein the orthogonal code hopping pattern is allocated to the second communication stations from the first communication station when starting communication, and the second communication stations give back the orthogonal code hopping pattern when the communication is completed.

10. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 3, further comprising the step of:

performing the orthogonal code hopping multiplexing for a channel among the channels, which has a low transmission data activity.

11. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 3, further comprising the step of:

transmitting a command for controlling transmission power of the second communication stations with use of a separate common power control channel of the first communication station.

14. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 3,

wherein the orthogonal code hopping patterns are generated with use of a pseudo-noise sequence generator.

16. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 3,

wherein a plurality of the orthogonal code hopping patterns for the statistical multiplexing are allocable to one of the second communication stations according to a send data rate of the first communication station.

P21950.A01

19. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 3,

wherein the orthogonal code hopping patterns are periodically repeated in a frame unit.

28. (Amended-Clean Text) The method for orthogonal code hopping multiplexing communications as claimed in claim 21,

wherein the hopping pattern collision is prevented only when there is a possibility that sending antenna beams of the first communication station, where the hopping patterns are collided, are superposed so to cause a serious error in a channel decoding process of the second communication station.

40. (Amended-Clean Text) The method for band spreading communications as claimed in claim 36,

wherein the first orthogonal code symbol group consists of child codes generated from one parent code in a hierarchical orthogonal code generating tree structure according to the variable spreading factors; and

wherein the second orthogonal code symbol group consists of remained orthogonal code symbols.

P21950.A01

41. (Amended-Clean Text) The method for band spreading communications as claimed in claim 36,

wherein the first orthogonal code symbol group used for the code division multiplexing is selected to have a variable spreading gain according to a send data rate.

43. (Amended-Clean Text) The method for band spreading communications as claimed in claim 36,

wherein the channel for the orthogonal code hopping multiplexing has a fixed data rate,

the method further comprising the step of selecting orthogonal code symbols having the same spreading factor in the second orthogonal code symbol group.


REMARKS

By the above amendment, the claims have been amended to delete multiple dependency.

If there should be any questions, the Examiner is invited to contact the undersigned at the telephone number listed below.

February 4, 2002
GREENBLUM & BERNSTEIN, P.L.C.
1941 Roland Clarke Place
Reston, VA 20191
(703) 716-1191

Respectfully submitted,
Dan-Keun SUNG et al.


Bruce H. Bernstein
Reg. No. 29,027
33,329

MARKED-UP COPY OF AMENDED CLAIMS

5. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 1 [one of claims 1 to 4],
wherein the orthogonal code is a Hadamard code.

6. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 1 [one of claims 1 to 4],
wherein the orthogonal code is a variable spreading factor code.

7. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 1 [one of claims 1 to 4],
wherein the orthogonal code is a gold code.

8. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 3 [one of claims 3 and 4], further comprising the step of:

allocating the orthogonal code hopping pattern to the second communication stations
dedicately.

9. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 3 [one of claims 3 and 4],

wherein the orthogonal code hopping pattern is allocated to the second communication stations from the first communication station when starting communication, and the second communication stations give back the orthogonal code hopping pattern when the communication is completed.

10. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 3 [one of claims 3 and 4], further comprising the step of:

performing the orthogonal code hopping multiplexing for a channel among the channels, which has a low transmission data activity.

11. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 3 [one of claims 3 and 4], further comprising the step of:

transmitting a command for controlling transmission power of the second communication stations with use of a separate common power control channel of the first communication station.

P21950.A01

14. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 3 [one of claims 3 and 4],

wherein the orthogonal code hopping patterns are generated with use of a pseudo-noise sequence generator.

16. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 3 [one of claims 3 and 4],

wherein a plurality of the orthogonal code hopping patterns for the statistical multiplexing are allocable to one of the second communication stations according to a send data rate of the first communication station.

19. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 3 [one of claims 3 and 4],

wherein the orthogonal code hopping patterns are periodically repeated in a frame unit.

28. (Amended) The method for orthogonal code hopping multiplexing communications as claimed in claim 21 [one of claims 21 to 27],

wherein the hopping pattern collision is prevented only when there is a possibility that sending antenna beams of the first communication station, where the hopping patterns are

P21950.A01

collided, are superposed so to cause a serious error in a channel decoding process of the second communication station.

40. (Amended) The method for band spreading communications as claimed in claim 36 [one of claims 36 to 39],

wherein the first orthogonal code symbol group consists of child codes generated from one parent code in a hierarchical orthogonal code generating tree structure according to the variable spreading factors; and

wherein the second orthogonal code symbol group consists of remained orthogonal code symbols.

41. (Amended) The method for band spreading communications as claimed in claim 36 [one of claims 36 to 39],

wherein the first orthogonal code symbol group used for the code division multiplexing is selected to have a variable spreading gain according to a send data rate.

43. (Amended) The method for band spreading communications as claimed in claim 36 [one of claims 36 to 39],

wherein the channel for the orthogonal code hopping multiplexing has a fixed data rate,

P21950.A01

the method further comprising the step of selecting orthogonal code symbols having the same spreading factor in the second orthogonal code symbol group.

20190320 05:05:00

**METHOD AND APPARATUS FOR ORTHOGONAL CODE HOPPING
MULTIPLEXING COMMUNICATIONS**

TECHNICAL FIELD

5 The present invention relates to an apparatus and a method for statistically multiplexing channels by using an orthogonal code hopping in a wire/wireless communications system where a plurality of the channels synchronized through one media and having a low data activity coexist. More particularly, the present invention relates to an

10 apparatus and a method in which, in a system having a first communication station and a plurality of second communication stations synchronized with the first communication station, the first communication station recognizes a channel toward each second communication station with an orthogonal code hopping pattern, the

15 orthogonal code hopping pattern of the second communication stations is determined at random, orthogonal code symbols in the hopping patterns of different channels may coincide at an instance (hereinafter, the above coincidence of the orthogonal code symbols is referred as "hopping pattern collision"), the system inspects send data symbols for

20 all send channels of the first communication station related with the collision and makes a corresponding data symbol interval OFF if any channel sends a data symbol not coincident with other channels, and

transmission power of all channels where transmission of the data symbol is OFF as much as an amount and during an interval defined in a communication protocol in order to supplement average bit energy of loss data in all relevant channels.

5

BACKGROUND ART

Descriptions in this application are based on a wireless communication communications system, however the statistical multiplexing suggested in the application may be applied to a wire
10 communications system as well as the wire communications system without any change.

In order to point out clearly which parts or concepts are developed or improved in the present invention in comparison with the prior art, a prior art is described on basis of a communication
15 communications system IS-95, which is already in service.

The first communication station and the second communication in this application are corresponding to a base station and a mobile station in a conventional system. One first communication station communicates with a plurality of second communication stations and
20 the present invention suggests a statistical multiplexing, which may be applied to a synchronized channel group having an orthogonality from the first communication station toward the second communication

stations. For a system, which maintains the orthogonality only for each channel group, such as Quasi-Orthogonal Code (QOC) adapted to Code Division Multiplexing Access (CDMA) 2000, which is one of candidate techniques for the next generation mobile communications system "the
5 IMT-2000 (International Mobile Telecommunications-2000)", the present invention may be independently implemented for each channel group. Moreover, when classifying channels of the first communication station such as sectored or smart antenna systems into channel groups having the same send antenna beam, the present invention may be
10 independently implemented in each channel group.

In the communications method by OCDM (Orthogonal Code Division Multiplexing) adapted by the conventional IS-95 system, the first communication station allocates orthogonal code symbols, which has not been allocated among the orthogonal codes when establishing a
15 call, to one of the second communication stations and the second communication station gives back the allocated orthogonal code symbols to the first communication station when releasing the call such that other second communication stations may use the orthogonal code symbols.

20 In description of the prior art, same reference number is used for a component having same function as that of the present invention.

FIG. 1 shows a system according to both the prior art and the

present invention. As shown in the figure, each communication channel 121, 122, 123 from the first communication station 101 to the second communication stations 111, 112, 113 is synchronized with maintaining orthogonality.

5 FIG. 2a shows configurations of a transmitter of the first communication station, which corresponds to a common element of the prior art and embodiments of the present invention. FIG. 2b shows configurations of the transmitter of the first communication station for a traffic channel of the prior art.

10 A pilot channel 200 is used as a reference signal for initial synchronous detection and tracking and synchronous decoding in the second communication station of FIG. 1. The pilot channel 200 is commonly used in all second communication stations in an area covered by the first communication station. The pilot channel 200
15 provides a phase reference for the synchronous decoding by transmitting symbols having a known pattern without passing through channel coding and channel interleaving as shown in FIG. 2a.

A synchronous channel 210 is a broadcast channel which is one-sidedly transmitted to all second communication stations in an area
20 covered by the first communication station, like the pilot channel 200. The first communication station transmits information (e.g. visual information, an identifier of the first communication station, etc.),

which the second communication stations commonly require, to the second synchronous channel 210 through the synchronous channel 210. The data from the synchronous channel 210 pass through a convolutional encoder 214, a repeater 216 for adjusting a symbol rate, a
5 block interleaver 218 for correcting an error burst and a repeater 219 for matching a send data symbol rate and are then transmitted to a spreading and modulating unit, shown in FIG. 3 and described below.

A paging channel 220 is a common channel used in case of an incoming message to the second communication station or for
10 answering to a request of the second communication station. A lot of the paging channels 220 can exist. The data transmitted to the paging channel pass through a convolutional encoder 224, a symbol repeater 226 and a block interleaver 228 and passes through an exclusive OR gate 236 together with an output of a long code generator 232 generated
15 by a long code mask 230. The data through the exclusive OR gate 236 is then transmitted to the spreading and modulating unit of FIG. 3.

A traffic channel 240 in FIG. 2b is a channel dedicatedly allocated to each second communication station for use until the call is completed. When there are data to be transmitted to each second
20 communication station, the first communication station transmits the data through the traffic channel 240. The data from the traffic channel 240 passes through a cyclic redundancy check (CRC) 241 for inspecting

an error in a specific time unit, or frame, (e.g. 20ms in IS-95). Tail bits 242 are inserted into the traffic channel, all of which are "0", and the data through the CRC 241 pass through a convolutional encoder 244 for ensuring to independently encoding the channel in a frame unit.

5 The data then pass through a symbol repeater 246 for matching transmission data symbol rate according to a send data rate. After passing through the symbol repeater 246, the data pass through a block interleaver 248 for changing an error burst into a random error. The data passing through the block interleaver 248 are scrambled in a
10 scrambler 256 with use of a pseudo-noise (PN) sequence, generated by passing an output of a long code generator 232 decimated in a decimator 234 with use of a long code mask 250 generated by an electronic serial number (ESN) allocated to each second communication station. A PCB (page control block) position extractor 258 extracts a
15 position where a command for controlling transmission power from the second communication station is inserted in the PN sequence decimated in the decimator 234. A punch and insert 260 punches a data symbol corresponding to the insert position of the power control command extracted by the PCB position extractor 258 among the data
20 symbols scrambled in the scrambler 256 and inserts the power control command, then transmitting the power control command to the spreading and modulating unit in FIG. 3.

FIGs. 3a, 3b and 3c show an embodiment of a spreading and modulating unit according to the prior art.

FIG. 3a corresponds to the commonly used IS-95 method employing BPSK (Binary Phase Shift Keying) as a data modulating
5 method. FIG. 3b shows the spreading and modulating unit employing QPSK (Quadrature Phase Shift Keying) as a data modulating method for transmitting double data in comparison the method in FIG. 3a.

FIG. 3b is adapted the CDMA 2000 method, which is one of candidate techniques for the IMT-2000. FIG. 3c shows a spreading and
10 modulating unit, which employs QOC (Quasi-Orthogonal Code) used in CDMA 2000, which is one of candidate techniques for the IMT-2000. In FIG. 3, signal converters 310, 326, 330, 346, 364 convert logic signals "0" and "1" into physical signal "+1" and "-1" to be really transmitted. Each channel of FIG. 2 passes through the signal converters and is
15 then spread in spreaders 312, 332 by an output of a Walsh code generator 362. Transmission power of each channel is adjusted in amplifiers 314, 334. All channels of the first communication station are spread in spreaders 314, 334 by an orthogonal Walsh function of the Walsh code generator 362 allocated to each channel fixedly. The
20 channels are then amplified in the amplifiers 314, 334 and then pass through QPSK spreading and modulating units 318, 338. Signals spread and modulated in the QPSK spreading and modulating units

318, 338 are multiplied by a carrier in multipliers 322, 342 to transit to a sending band through low-pass filters (LPF) 320, 340. The signal multiplied by the carrier passes through a radio communication unit and is then transmitted through an antenna, not shown in the figures.

5 FIG. 3b is identical to FIG. 3a except the fact that, in order to transmit the signal generated in FIG. 2 to QPSK instead of BPSK, different information data are carried in an in-phase channel and a quadrature phase channel through a demultiplexer 390. Using the demultiplexer 390 and the signal converters 310, 330 enables QAM
10 (Quadrature Amplitude Modulation) as well as QPSK.

FIG. 3c shows the case that a QOC mask is used for distinguishing a channel from the first communication station to the second communication stations. Orthogonality is not maintained in a code symbol group using different QOC masks but maintained in a code
15 symbol group using same QOC mask. Therefore, the present invention is applied to the orthogonal code symbol group using same QOC mask, which may maintain the orthogonality.

FIGs. 4a, 4b and 4c shows signals used in the code division multiplexing, which spreads the signal generated in FIG. 2 and FIG. 3
20 into the orthogonal code symbol fixedly allocated to each channel, according to the prior art. A pilot channel 410 is spread by a fixedly allocated orthogonal Walsh code symbol W#0 in a spreader 412. Other

channels are also spread by orthogonal Walsh code symbols W#1, W#2, W#29, W#30, W#63 fixedly allocated regardless of activities of the corresponding channels. If allocating the orthogonal code symbol fixedly to a channel such as channels 440, 450, 460 having relatively
5 low transmission data activity, utilization of the orthogonal code, which is a limited source, is much less than 100%.

FIG. 4b shows how a despreading data symbol is spread by the orthogonal code. In reference numbers 471 to 477, white areas mean "0[+1]" and black areas mean "1[-1]", for the Walsh code as an example
10 of the orthogonal code.

FIG. 4c shows that the orthogonal code symbols are allocated to each channel in OCDM.

FIG. 5 briefly shows a configuration of a receiver of the second communication station corresponding to the transmitter of the first
15 communication station according to the prior art. As shown in the figure, the signal received through the antenna passes through multipliers 510, 530 for multiplying the signal with a carrier, low pass filters (LPFs) 512, 532 for generating a baseband signal and short code generators 520, 540 for synchronizing the signal with a sequence same
20 as the PN sequence used in the transmitter. The signal then passes through multipliers 514, 534 for multiplying the signal by the received baseband signal and then despreaders 516, 536 for accumulating the

signals during a transmission data symbol area. A channel estimator 550 estimates a transmission channel by extracting only pilot channel components from the baseband signal as the orthogonal code symbol allocated to the pilot channel. A phase recovery 560 compensates
5 phase distortion of the baseband signal with use of an estimated phase distortion value.

FIG. 6 shows a configuration of a receiver for a channel in which a control command for controlling transmission power from the second communication station to the first communication station like the
10 paging channel is not inserted. Referring to the figure, maximum ratio combiners 610, 612 combine signals passing through the phase compensation to a maximum ratio. If the receiver performs QPSK data modulation as shown in FIG. 3b, the receiver performs descrambling by multiplexing the signal in a multiplexer 614, performing soft decision in
15 a soft decision unit 616, then decimating an output of a long code generator 622 generated by a long code mask 620 in a decimator 624, and then multiplying the signal through the soft decision unit with a decimated result of the decimator 624. In the present invention, a configuration of a receiver in the second communication station for the
20 orthogonal code hopping multiplexing is similar to the configuration in FIG. 6. For the synchronous channel, the descrambling processes 620, 622, 624, 626, 628 using the long code may be skipped.

FIG. 7 shows a configuration of a receiver to which a control command for controlling transmission power from the second communication station to the first communication station like the traffic channel. As shown in the figure, the signal enduring the phase compensation in FIG. 5 passes through maximum ratio combiners 710, 712. In case that a receiver performs QPSK data modulation as shown in FIG. 5, a multiplexer 714 multiplexes a in-phase component and an orthogonal phase component in the signal. An extractor 740 extracts a signal component corresponding to the power control command transmitted from the first communication station among the received signal. The signal from the extractor 740 then passes through a hard decision unit 744 and is then transmitted to a transmission power controller of the second communication station. Data symbols except the power control command in the received signal from the multiplexer 714 pass through a soft decision unit 742. A decimator 724 decimates an output of a long code generator 722 generated by a long code mask 720 generated by an identifier of the second communication station. The data symbols from the soft decision unit 742 is then multiplied in a multiplier 718 by a result of the decimator 724, so to perform descrambling.

FIG. 8 shows a function of recovering the received signal through the signal processes of FIG. 6 and FIG. 7 from the first communication

station, through block deinterleavers 818, 828, 838 and convolutional decoders 814, 824, 834. In a synchronous channel 810, in order to lower a symbol rate, a sampler 819 performs symbol compression for the signals through the soft decision unit by accumulating the signals, which is an inverse process to the symbol repeater 219. The signal through the sampler 819 passes through a block deinterleaver 818. Then, a sampler 816 performs symbol compression again for the signal, which is an inverse process to the symbol repeater 216, before the signal passes to a convolutional decoder 814. The signal passing enduring the symbol compression then passes through the convolutional decoder 814, then recovering the synchronous channel transmitted from the first communication station.

In case of a paging channel 820, the signal enduring the soft decision passes through a block deinterleaver 828 for channel interleaving. The signal enduring the channel interleaving passes through a sampler 826 for symbol compression according to the send data rate, which is an inverse process of the symbol repeater 226. The signal enduring the symbol compression passes through a convolution decoder 824 for channel decoding, so recovering the paging channel transmitted from the first communication station.

In case of a traffic channel 830, the signal enduring the soft decision passes through a block deinterleaver 838 for performing

channel deinterleaving regardless of a send data rate. The signal enduring the channel interleaving passes through a sampler 836 for performing symbol compression according to the send data rate, which is an inverse process to the symbol repeater 246. A convolutional
5 decoder 834 performs channel decoding for the signal enduring the symbol compression. A tail bit remover 832 removes tail bits of the signal used for independent send signal generation in a frame unit. A CRC 831 generates a CRC bit for the send data portion like the transmitter and inspects errors by comparison with a recovered CRC
10 after channel decoding. If the two CRC bits coincides, the CRC 831 determines that there is no error and then the traffic channel data are recovered. If the transmitter does not include information about the send data rate in 20ms frame unit, the send data rate of the first communication station may be determined by channel-decoding the
15 signals enduring the independent channel deinterleaving and comparing the CRC bits. A system, which transmits a send data rate independently, just further requires a channel decoding process corresponding to the data rate.

In case of spreading the desreading data symbol by fixedly using
20 the orthogonal code allocated when establishing a call as shown in FIG. 3 in order to maintain orthogonality between channels from the first communication station to the second communication station as shown

in FIG. 1, the orthogonal code, limited source, may not be efficiently used for send data having relatively low activity such as data indicated by reference numbers 440, 450 and 460 in FIG. 4a. In order to increase activity of the orthogonal code with fixed allocation, rapid channel allocation and return are required. However, if transmitting the control signal information for channel allocation and return more frequently, more significant amounts of limited frequency resources should be used for the control information of data transmission, not for data transmission itself. Moreover, however rapid the channel allocation and return are processed, there should be a buffering process after the data to be transmitted reaches at the first communication station till transmitted in order to transmit a channel allocation (or return) message and respond to the message. As time for such processes is extended, more capacity is required in the buffer. Information, which requires checking whether the information is transmitted normally, should be buffered for retransmission. However, in case of transmitting information without checking normal transmission of the information, such as, in a datagram method, a delay should be minimized in an allowable range in order to decrease the capacity of the buffer.

Therefore, while the prior art allocates the orthogonal codes in a fixed manner so to have 1:1 relation between the orthogonal code and the channel, the present invention, with a little modification of the prior

art, performs statistical multiplexing for traffic channels having low activities in consideration of activity of the send data in order to increase activities of the orthogonal codes, which are limited resources, and eliminates unnecessary channel allocating and returning processes
5 in order to decrease buffer capacity and data transmission delay.

DISCLOSURE OF INVENTION

The present invention is designed to overcome the above problems of the prior art. An object of the invention is to decrease waste of
10 resources caused by transmission of unnecessary control signals, minimize a required capacity of a buffer in a first communication station used for time division multiplexing and reduce a data transmission delay by means of utilizing the limited resources efficiently with use of a statistical multiplexing method, namely orthogonal code
15 hopping multiplexing, when synchronized channels maintaining orthogonality have low activities, and performing spreading or despreading according to a hopping pattern of each transmitter and receiver by skipping unnecessary channel allocating and returning processes.

20 In order to accomplish the above object, the present invention provides a method for orthogonal code hopping multiplexing communications in a band spreading communications system, which

performs statistical multiplexing for communication channels from a first communication station to second communication stations by orthogonal code hopping multiplexing communications.

5 The channels from the first communication station to a plurality of the second communication stations may be synchronized to distinguish the channels by using orthogonality.

The method may include a further step of distinguishing the channels from the first communication station to the second communication stations with use of orthogonal code hopping patterns.

10 The orthogonal code may be a Hadamard code, a variable spreading factor code or a gold code.

The method may include a further step of allocating the orthogonal code hopping pattern to the second communication stations dedicatedly.

15 It is preferred that the orthogonal code hopping pattern is allocated to the second communication stations from the first communication station when starting communication, and the second communication stations give back the orthogonal code hopping pattern when the communication is completed.

20 The method may include a further step of performing the orthogonal code hopping multiplexing for a channel among the channels, which has a low transmission data activity.

The method may include a further step of transmitting a command for controlling transmission power of the second communication stations with use of a separate common power control channel of the first communication station.

- 5 The transmission power control command of each second communication station in the common power control channel can be time-multiplexed and may employ a collision-resistant hopping pattern for preventing collision of the hopping pattern.

- 10 The collision-resistant hopping pattern may include a fixed orthogonal code symbol allocation like a code division multiplexing.

The orthogonal code hopping patterns for the statistical multiplexing may be generated at random or with use of a pseudo-noise sequence generator.

- 15 A plurality of the orthogonal code hopping patterns for the statistical multiplexing are allocable to one of the second communication stations according to a send data rate of the first communication station.

- 20 Each of the orthogonal code hopping patterns may hop independently in the orthogonal code hopping multiplexing communications.

The orthogonal code hopping patterns may hop not to generate collision each other in the orthogonal code hopping multiplexing

communications and may be periodically repeated in a frame unit.

The frame unit is an independent data unit based on channel encoding.

The first communication station may detect a hopping pattern
5 collision caused by the random orthogonal code hopping patterns in
advance in order not to transmit a corresponding despread data
symbol.

The method may include a further step of comparing despread
data symbols at time of a hopping pattern collision caused by the
10 random orthogonal code hopping patterns in order to transmit the data
symbols in case that all of the data symbols are same.

The method may include a further step of comparing despread
data symbols at time of a hopping pattern collision caused by the
random orthogonal code hopping patterns in order not to transmit the
15 data symbols in case that the data symbols are not same.

The method may include a further step of increasing transmission
power of a data symbol next to the data symbols, which are not
transmitted because of discordance of the despread data symbols at
time of the hopping pattern collision.

20 It is also preferred that the transmission power is increased as
much as an amount given by a system parameter during a period given
by a system parameter.

The two system parameters may be position functions of the not-transmitted despread data symbols and preferably at least 0.

Preferably, the hopping pattern collision is prevented only when there is a possibility that sending antenna beams of the first communication station, where the hopping patterns are collided, are superposed so to cause a serious error in a channel decoding process of the second communication station.

A pilot signal can be used for initial synchronous gain and tracking of the channels and synchronous decoding of the channels owing to phase distortion compensation.

The pilot signal may employ a non-collision hopping pattern for preventing a loss of the phase distortion compensation ability due to collision.

The non-collision hopping pattern may include a fixed orthogonal code symbol allocation like the code division multiplexing.

In order to obtain the above object, the present invention provides a transmitter in a band spreading communications system including a first communication station and a second communication station, the transmitter comprising a channel encoder for coding a channel; an orthogonal code hopping pattern generator for generating an orthogonal code hopping pattern; an orthogonal code generator for generating an orthogonal code symbol according to the hopping pattern; and an

orthogonal code collision detector for detecting collision of the hopping patterns.

The transmitter may further include an interrupter for interrupting a send signal according to output of the orthogonal code
5 collision detector.

The orthogonal code collision detector may include a despread-
ing data symbol comparator for comparing that all of despread-
ing data symbols of corresponding channels are same at time of a hopping
pattern collision; and the interrupter may interrupt transmission of the
10 sending signal in case that the corresponding despread-
ing data symbols are not same as a comparison result of the despread-
ing data symbol separator.

In order to accomplish the above object, the present invention
provides a receiver in a band spreading communications system
15 including a first communication station and second communication
stations, the receiver comprising a channel decoder for decoding a
channel; an orthogonal code hopping pattern generator for generating
an orthogonal code hopping pattern; and an orthogonal code generator
for generating an orthogonal code symbol according to the hopping
20 pattern.

In order to perform the above object, the present invention also
provides a method for band spreading communications in a band

20100301 190.020402

spreading communications system using orthogonal codes, the method comprising the step of dividing the orthogonal codes into a first orthogonal code symbol group for code division multiplexing and a second orthogonal code symbol group for statistical multiplexing owing
5 to orthogonal code hopping.

The method may include a further step of performing the code division multiplexing by fixedly allocating the orthogonal code symbols in the first orthogonal code symbol group to a channel having a high data activity in communications.

10 The method may include a further step of performing orthogonal code hopping multiplexing for a channel having a low data activity according to the orthogonal code hopping pattern by using only the orthogonal code symbols in the second orthogonal code symbol group.

The orthogonal code may be an orthogonal variable spreading
15 factor code.

Preferably, the first orthogonal code symbol group consists of child codes generated from one parent code in a hierarchical orthogonal code generating tree structure according to the variable spreading factors, while the second orthogonal code symbol group consists of
20 remained orthogonal code symbols.

The first orthogonal code symbol group used for the code division multiplexing may be selected to have a variable spreading gain

according to a send data rate.

The channel for the orthogonal code hopping multiplexing may have a fixed data rate, and the method may include a further step of selecting orthogonal code symbols having the same spreading factor in
5 the second orthogonal code symbol group.

BRIEF DESCRIPTION OF THE DRAWINGS

These and other features, aspects, and advantages of preferred embodiments of the present invention will be more fully described in the
10 following detailed description, taken accompanying drawings. In the drawings:

FIG. 1 shows a concept of a system having a first communication station and second communication stations according to both the prior art and the present invention;

15 FIG. 2a shows a configuration of a transmitter in the first communication station, which is a common component of the prior art and the present invention;

FIG. 2b shows a configuration of a transmitter for traffic channels in the first communication station according to the prior art;

20 FIG. 3a shows a configuration of a receiver in the first communication station using a CDMA method in case of BPSK data modulation according to the prior art;

FIG. 3b shows a configuration of a receiver in the first communication station using a CDMA method in case of QPSK data modulation according to the prior art;

FIG. 3c shows a configuration of a receiver in the first
5 communication station using a CDMA method in case of using QOC data according to the prior art;

FIG. 4a shows a send signal of the first communication station according to the prior art;

FIG. 4b shows an orthogonal code for distinguishing channels
10 according to the prior art;

FIG. 4c shows the CDMA according to the prior art;

FIG. 5 shows a configuration of a receiver in the second communication station in the CDMA method according to the prior art;

FIG. 6 shows a configuration of common components of the
15 receiver in the second communication station according to the prior art and the present invention;

FIG. 7 shows a configuration of the receiver in the second communication station in FIG. 4b;

FIG. 8 shows a configuration of common components of the
20 receiver according to the prior art and the present invention;

FIG. 9 shows a configuration of a transmitter in the first communication station about traffic channels for orthogonal code

hopping multiplexing and a configuration of a common power control channel for the traffic channels;

FIG. 10a shows a configuration of a transmitter in the first communication station using the orthogonal code hopping multiplexing according to the present invention, corresponding to FIG. 4a;

FIG. 10b shows a configuration of a transmitter in the first communication station using the orthogonal code hopping multiplexing according to the present invention, corresponding to FIG. 4b;

FIG. 10c shows a configuration of a transmitter in the first communication station using the orthogonal code hopping multiplexing according to the present invention, corresponding to FIG. 4c;

FIG. 11 shows a configuration of an orthogonal code hopping pattern generator according to the present invention;

FIG. 12a shows an example of an orthogonal variable spreading factor code according to the present invention;

FIG. 12b shows an orthogonal gold code generator according to the present invention;

FIG. 13 shows a configuration of a receiver in the second communication station in the orthogonal code hopping multiplexing of FIG. 10b according to the present invention;

FIG. 14a shows a send signal when using the code division multiplexing for traffics toward the second communication station

having relatively high send data activities;

FIG. 14b shows a send signal when using the orthogonal code hopping multiplexing for traffics toward the second communication station having relatively low send data activities;

5 FIG. 14c shows the orthogonal spreading code of the present invention;

FIG. 14d shows the code division multiplexing of FIG. 14a according to the present invention;

FIG. 14e shows the statistical multiplexing by the orthogonal code hopping multiplexing of FIG. 14b according to the present invention;

FIG. 14f shows hopping pattern collisions in case of the orthogonal code hopping multiplexing of FIG. 14b according to the present invention;

FIG. 14g shows transmission stopping in the collision area of relevant channels when the hopping patterns collide and send data symbols do not match as shown in FIG. 14f;

FIG. 14h shows the process of increasing transmission power of the first communication station in a certain area after a data symbol not transmitted in order to compensate average receiving energy required for a channel decoder for satisfied communication quality when stopping transmission in the hopping pattern collision area in FIG. 14g; and

FIG. 15 is a diagram for illustrating that transmission stopping caused by the hopping pattern collision and mismatch of the send data symbols is independently operated for each send antenna beam of the first communication station.

5

BEST MODES FOR CARRYING OUT THE INVENTION

Hereinafter, preferred embodiments of the present invention will be described in detail with reference to the accompanying drawings.

10 In this application, similar reference numbers are used for components similar to the prior art and only modified or added components in comparison with the prior art are described for the present invention in detail.

FIG. 9 is a modified one of the traffic channel of the prior art for performing orthogonal code hopping multiplexing in case of having a low send data activity, which is identical to the prior art except that a transmission power control command for the second communication station is inserted. Communication is divided into bi-directional communication and one-directional communication, in which the one-directional communication does not need the transmission power control command for the second communication station.

15

20

However, in case of the bi-directional communication, the

transmission power control command is required in order to maximize system capacity through effective power control. For improving a processing rate, the power control command does not endure channel coding in most cases. A random orthogonal code hopping pattern
5 inevitably causes collisions between each other channels. Therefore, it is required to transmit the power control command to a channel in which a collision is generated. In this point, a concept of a common power control channel adapted in CDMA 2000, which is one of candidate techniques for the IMT-2000, may be introduced. The
10 common power control channel is spread by a separate orthogonal code symbol such as the pilot channel and transmitted by the time division multiplexing for a plurality of the second communication stations. A position of the power control command for each second communication station is allocated in a call establishing process. FIG. 9 shows an
15 embodiment of the common power control channel for controlling 24 second communication stations.

FIGs. 10a, 10b and 10c show embodiments to which characteristics of the present invention are applied to the prior art shown in FIGs. 3a, 3b and 3c. For statistical multiplexing by the
20 orthogonal code hopping multiplexing suggested in the present invention, required are an orthogonal code hopping pattern generator 380 and collision comparator & controller 384, 386 for suitable control

204020"06T0E00T
10030190"02040E
by detecting collisions of the orthogonal code symbols generated by the random hopping pattern generation. An example of the orthogonal code hopping pattern generator is shown in FIG. 11, which has a configuration for generating the hopping pattern with use of a general
5 PN sequence generator. There is required an orthogonal code generator 382 for generating a spreading orthogonal code symbol according to the hopping pattern generator 380. The orthogonal code generated in the orthogonal code generator 382 may be an orthogonal variable spreading factor (OVSF) having a hierarchical structure which can be a Walsh
10 code for a specific spreading factor as shown in FIG. 12a, or an orthogonal gold code generated by an orthogonal gold code generator as shown in FIG. 12b. Any orthogonal code maintaining orthogonality is possible.

When an output of the orthogonal code hopping pattern generator
15 380 is constant, the present invention equals to the orthogonal code division multiplexing identical to the prior art. That is, the orthogonal code division multiplexing of the prior art is a subset of the orthogonal code hopping multiplexing of the present invention. Therefore, after dividing one orthogonal code into two orthogonal code symbol groups,
20 one orthogonal code group is used for an orthogonal code hopping multiplexing using fixed allocation and the other orthogonal code group is used for an orthogonal code hopping multiplexing using a hopping

pattern.

Or else, one orthogonal code symbol group among the two divided
orthogonal code symbols performs the orthogonal code hopping
multiplexing with use of a hopping pattern intentionally selected to
5 prevent collision of the hopping patterns, while the other orthogonal
code symbol group performs the orthogonal code hopping multiplexing
by the statistical multiplexing with use of a hopping selected randomly
in which a collision between the hopping patterns may happen.

In the two cases, it is preferred that the former is allocated to a
10 channel having a relatively high send data activity and the later is
allocated to a channel having a relatively low send data activity. In case
of using a hierarchical orthogonal code supporting a variable spreading
gain as a spreading code as shown in FIG. 12a, it is preferred to divide
the orthogonal code into orthogonal code symbol groups 393, 397
15 consisting of all child code symbols having same parent code symbol
391, 395 such as "01" or "0110" because it may support the variable
spreading gain. As described above in brief, if the orthogonal code
hopping pattern generator intentionally generates the orthogonal code
hopping patterns not to select different channels at same orthogonal
20 code symbol in the same instant, no collision generates.

However, such method has disadvantages that the hopping
pattern should be allocated by the first communication station in

establishing a call and that number of the hopping patterns allocated by the first communication station is limited by a size of the orthogonal code. In this case, because the statistical multiplexing according to the data activity of each channel is not possible, hopping patterns are
5 allocated to each channel independently and at random. In this reason, orthogonal code patterns, which select the same orthogonal code symbol at the same instant, make a collision inevitably. Therefore, the present invention receives hopping patterns of each channel and despreads data symbols to be transmitted and determines whether
10 the hopping patterns collide with use of the collision comparator & controller 384, 386 for overcoming such problems. Besides that, the present invention compares whether the despreads data symbols of all channels corresponding to the collisions are all same.

In case that all despreads data symbols match, the data
15 symbols in the collision area are spread and transmitted. It is because the data symbol may cause an error in the channel decoding process. However, if there is one data symbol not matched, the data symbol in the collision area of the corresponding channel is not transmitted. That is, according to a result of the collision comparator & controller 384,
20 386, an input of the multipliers 385, 387 becomes "+1" or "0". In the area that the input of the multiplier is "0", the transmission is stopped.

In order to compensate deficiency of an average receiving energy

in the second communication station due to transmission stop of the
despreading data symbol for satisfied quality, a gain of amplifiers 315,
335 of the corresponding channel is adjusted as much as a size given
by a system parameter during an area given by a system parameter like
5 the reference numbers 1072, 1074 in FIG. 14h, then increasing the
transmission power of the first communication station. Regardless of
the above process, the transmission power control for the first
communication station is performed according to the method of the
prior art.

10 FIGs. 14a to 14h show concepts of a send signal of the first
communication station according to the present invention. FIG. 14a
shows a send signal in case of performing the code division multiplexing
by fixedly allocating the orthogonal code symbols to a channel which
transmits data having a relatively high activity. FIG. 14b shows a send
15 signal in case of performing the orthogonal code hopping multiplexing
to select a spreading orthogonal code symbol according to hopping
patterns $H_1[n]$, $H_2[n]$, $H_3[n]$, ..., $H_M[n]$ for a channel which transmits
data having a relatively low activity. The number of the hopping
patterns may be over a size of the orthogonal code. Because the
20 hopping patterns may cause collision when generating the hopping
patterns at random, it is preferred that the orthogonal code symbols are
fixedly allocated as designated by a reference number 912 to a pilot

channel 910 used as a phase reference for the synchronous demodulation and a channel not enduring channel coding such as the common power control channel of FIG. 9, while the orthogonal code hopping multiplexing is performed with use of remained orthogonal
5 code symbols.

It is also preferred to use the statistical multiplexing by the orthogonal code hopping multiplexing in a data area and not to use the orthogonal code hopping multiplexing in a pilot area not only when the pilot channel exists in the code division multiplexing method but also
10 when performing the time division multiplexing for the pilot signal like W-CDMA (Wideband Code Division Multiple Access), another candidate technique of the IMT-200 system. In the send data area, the orthogonal code symbol used in the pilot area may be also used.

If the send antenna beams from the first communication station
15 are different according to positions of the second communication stations such as smart antenna, the pilot signals are separately managed for each antenna beam. In addition, in an asynchronous modulation/demodulation system, which does not use the pilot signal and does not require the pilot signal, the orthogonal code hopping
20 multiplexing is performed with use of all orthogonal code symbols in the orthogonal code.

FIG. 14c shows an example of the orthogonal code symbol used

for spreading the despreading data symbol according to the present invention. As shown in the figure, it will be easily known that a symbol of this embodiment has no difference from the prior art in FIG. 4b except the case that a different orthogonal code is used.

5 FIG. 14d shows a case of fixedly allocating the orthogonal code symbols to each channel having a high send data activity similar to the prior art.

FIG. 14e shows the orthogonal code hopping multiplexing according to the present invention, in which the hopping channels in
10 each channel 1011, 1012, 1013, 1014, 1015, 1016, 1017 do not collide in all symbol areas 1021, 1022, 1023, 1024, 1025, 1026, 1027, 1028. However, in case of performing the orthogonal code hopping multiplexing as shown in FIG. 14h, it can be seen that the hopping patterns collide in the symbol areas 1041, 1043, 1046. In a time area
15 1041, the hopping patterns collide but the despreading data symbols coincide (shown with double-line box). Time areas 1043, 1046 is a case that the despreading data symbols do not coincide. Through the hopping patterns collide in the time areas 1043, 1046 as shown in FIG. 14g. however, in the case of time area 1061 where the send data
20 symbols coincide, corresponding despreading data symbols are spread and transmitted, while in the case of time areas 1063, 1066 where the send data symbols do not coincide, transmission of all relevant channel

is stopped.

Such channel stop is carried out for the channel group existing in same send antenna beam from the first communication station. In case that a plurality of send antenna beams 1120, 1130, 1140 from the first communication station such as a smart antenna exist, the transmission is not stopped for channels 1132, 1142, 1144 in non-overlapped send antenna beams 1130, 1140 though the hopping patterns collide.

FIG. 14h shows the process of increasing transmission power as much as a regulated amount during a regulated time in order to satisfy an average receiving signal energy in the second communication station required for communication quality after an area where the transmission is stopped due to collision of the hopping patterns and discordance of the despreading data symbols as described above in brief, similar to FIG. 14g.

As described in embodiments of the present invention, if performing the orthogonal code hopping multiplexing with random hopping patterns, the send data may be intentionally lost in an area where the hopping patterns collide. Therefore, in order to recover the data existing in the loss area in the receiver, it is essential that the transmitter performs the channel encoding and the receiver performs the channel decoding.

The statistical multiplexing of the present invention may be used

in combination with other multiplexing methods such as a time division multiplexing, a frequency division multiplexing, a space division multiplexing, etc.

In addition, as a development of the orthogonal code division
5 multiplexing system using a multi-code method, a plurality of channels may be allocated to one second communication station with use of a plurality of hopping patterns, which may realize a rapid send data rate. At this time, in allocating the multiple hopping patterns, the hopping patterns of each channel are generated as described above.

10 As described above, the present invention employs the statistical multiplexing method, namely the orthogonal code hopping multiplexing, in case that synchronized channels maintaining orthogonality have low activities, which may enable to use limited resources efficiently and increase less complexity than the prior art. The receiver particularly
15 needs no increase of hardware except the orthogonal code hopping pattern generator. In addition, because the receiver and the transmitter perform spreading and despreading according to the respective hopping patterns without any process for excessive channel allocation or return for a traffic having a low activity from the first communication station to
20 the second communication, the present invention may decrease waste of resources due to, such as, unnecessary control signal transmission and reduce buffer capacity and data transmission delay caused by

scheduling of the send data of the first communication.

Moreover, the present invention may distinguish nearly unlimited number of channels (if the hopping pattern has a period in a frame unit, near $6419.2\text{kps} \times 20\text{ms} = 64384$ of channels on basis of IS-95 system) when
5 selecting the hopping patterns at random in comparison to the method of allocating the spreading orthogonal code symbols fixedly. Furthermore, though there occurs collision between the spreading orthogonal code symbols due to the random selection of the hopping patterns, there is no need to stop transmission of the colliding
10 despread data symbol in case that the second communication station exists in an area where send antenna beams of, such as, a sectored antenna and a smart antenna are not overlapped. In addition, the data symbols, which is not transmitted due to the hopping pattern collision between channels in same send antenna beam, may be
15 recovered in the channel decoding process of the second communication station without informing to the second communication station.

The concept of the present invention may be applied to each carrier code group and each quasi-orthogonal code group in systems
20 using a multiple carrier transmission method, a quasi-orthogonal code, etc. to realize the statistical multiplexing.

What is claimed is:

1. A method for orthogonal code hopping multiplexing communications in a band spreading communications system, the
5 method comprising the step of:

performing statistical multiplexing for communication channels from a first communication station to second communication stations by orthogonal code hopping multiplexing communications.

10 2. The method for orthogonal code hopping multiplexing communications as claimed in claim 1,

wherein the channels from the first communication station to a plurality of the second communication stations are synchronized to distinguish the channels by using orthogonality.

15 3. The method for orthogonal code hopping multiplexing communications as claimed in claim 1, further comprising the step of:

distinguishing the channels from the first communication station to the second communication stations with use of orthogonal code
20 hopping patterns.

4. The method for orthogonal code hopping multiplexing

communications as claimed in claim 2, further comprising the step of:

distinguishing the channels from the first communication station to the second communication stations with use of orthogonal code hopping patterns.

5

5. The method for orthogonal code hopping multiplexing communications as claimed in one of claims 1 to 4,

wherein the orthogonal code is a Hadamard code.

10

6. The method for orthogonal code hopping multiplexing communications as claimed in one of claims 1 to 4,

wherein the orthogonal code is a variable spreading factor code.

15

7. The method for orthogonal code hopping multiplexing communications as claimed in one of claims 1 to 4,

wherein the orthogonal code is a gold code.

20

8. The method for orthogonal code hopping multiplexing communications as claimed in one of claims 3 and 4, further comprising the step of:

allocating the orthogonal code hopping pattern to the second communication stations dedicatedly.

204020"06T0E00T

9. The method for orthogonal code hopping multiplexing communications as claimed in one of claims 3 and 4,

wherein the orthogonal code hopping pattern is allocated to the
5 second communication stations from the first communication station
when starting communication, and the second communication stations
give back the orthogonal code hopping pattern when the
communication is completed.

10 10. The method for orthogonal code hopping multiplexing
communications as claimed in one of claims 3 and 4, further
comprising the step of:

performing the orthogonal code hopping multiplexing for a
channel among the channels, which has a low transmission data
15 activity.

11. The method for orthogonal code hopping multiplexing
communications as claimed in one of claims 3 and 4, further
comprising the step of:

20 transmitting a command for controlling transmission power of the
second communication stations with use of a separate common power
control channel of the first communication station.

12. The method for orthogonal code hopping multiplexing communications as claimed in claim 11,,

wherein the transmission power control command of each second
5 communication station in the common power control channel is time-multiplexed and employs a collision-resistant hopping pattern for preventing collision of the hopping pattern.

13. The method for orthogonal code hopping multiplexing
10 communications as claimed in claim 12,

wherein the collision-resistant hopping pattern includes a fixed orthogonal code symbol allocation like a code division multiplexing.

14. The method for orthogonal code hopping multiplexing
15 communications as claimed in one of claims 3 and 4,

wherein the orthogonal code hopping patterns for the statistical multiplexing is generated at random.

15. The method for orthogonal code hopping multiplexing
20 communications as claimed in claim 14,

wherein the random code hopping patterns are generated with use of a pseudo-noise sequence generator.

16. The method for orthogonal code hopping multiplexing communications as claimed in one of claims 3 and 4,

wherein a plurality of the orthogonal code hopping patterns for
5 the statistical multiplexing are allocable to one of the second communication stations according to a send data rate of the first communication station.

17. The method for orthogonal code hopping multiplexing
10 communications as claimed in claim 16,

wherein each of the orthogonal code hopping patterns hops independently in the orthogonal code hopping multiplexing communications.

18. The method for orthogonal code hopping multiplexing
15 communications as claimed in claim 16,

wherein the orthogonal code hopping patterns hop not to generate collision each other in the orthogonal code hopping multiplexing communications.

20

19. The method for orthogonal code hopping multiplexing communications as claimed in one of claims 3 and 4,

wherein the orthogonal code hopping patterns are periodically repeated in a frame unit.

20. The method for orthogonal code hopping multiplexing
5 communications as claimed in claim 19,

wherein the frame unit is an independent data unit based on channel encoding.

21. The method for orthogonal code hopping multiplexing
10 communications as claimed in claim 14,

wherein the first communication station detects a hopping pattern collision caused by the random orthogonal code hopping patterns in advance in order not to transmit a corresponding despread data symbol.

15

22. The method for orthogonal code hopping multiplexing communications as claimed in claim 14, further comprising the step of:

comparing despread data symbols at time of a hopping pattern collision caused by the random orthogonal code hopping patterns in
20 order to transmit the data symbols in case that all of the data symbols are same.

23. The method for orthogonal code hopping multiplexing communications as claimed in claim 14, further comprising the step of:

comparing despread data symbols at time of a hopping pattern collision caused by the random orthogonal code hopping patterns in order not to transmit the data symbols in case that the data symbols are not same.

24. The method for orthogonal code hopping multiplexing communications as claimed in claim 23, further comprising the step of:

increasing transmission power of a data symbol next to the data symbols, which are not transmitted because of discordance of the despread data symbols at time of the hopping pattern collision.

25. The method for orthogonal code hopping multiplexing communications as claimed in claim 24,

wherein the transmission power is increased as much as an amount given by a system parameter during a period given by a system parameter.

26. The method for orthogonal code hopping multiplexing communications as claimed in claim 25,

wherein the two system parameters are position functions of the

not-transmitted despread data symbols.

27. The method for orthogonal code hopping multiplexing communications as claimed in claim 26,

5 wherein the two system parameters are at least 0.

28. The method for orthogonal code hopping multiplexing communications as claimed in one of claims 21 to 27,

204020" 05T000T
10 wherein the hopping pattern collision is prevented only when there is a possibility that sending antenna beams of the first communication station, where the hopping patterns are collided, are superposed so to cause a serious error in a channel decoding process of the second communication station.

15 29. The method for orthogonal code hopping multiplexing communications as claimed in claim 28,

wherein a pilot signal is used for initial synchronous gain and tracking of the channels and synchronous decoding of the channels owing to phase distortion compensation.

20

30. The method for orthogonal code hopping multiplexing communications as claimed in claim 29,

wherein the pilot signal employs a non-collision hopping pattern for preventing a loss of the phase distortion compensation ability due to collision.

5 31. The method for orthogonal code hopping multiplexing communications as claimed in claim 30,

wherein the non-collision hopping pattern includes a fixed orthogonal code symbol allocation like the code division multiplexing.

10 32. A transmitter in a band spreading communications system including a first communication station and a second communication station, the transmitter comprising:

a channel encoder for coding a channel;

15 an orthogonal code hopping pattern generator for generating an orthogonal code hopping pattern;

an orthogonal code generator for generating an orthogonal code symbol according to the hopping pattern; and

an orthogonal code collision detector for detecting collision of the hopping patterns.

20

33. The transmitter as claimed in claim 32, further comprising an interrupter for interrupting a send signal according to output of the

orthogonal code collision detector.

34. The transmitter as claimed in claim 33,

wherein the orthogonal code collision detector includes a
5 despread data symbol comparator for comparing that all of
despread data symbols of corresponding channels are same at time
of a hopping pattern collision; and

wherein the interrupter interrupts transmission of the sending
signal in case that the corresponding despread data symbols are not
10 same as a comparison result of the despread data symbol separator.

35. A receiver in a band spreading communications system
including a first communication station and second communication
stations, the receiver comprising:

15 a channel decoder for decoding a channel;

an orthogonal code hopping pattern generator for generating an
orthogonal code hopping pattern; and

an orthogonal code generator for generating an orthogonal code
symbol according to the hopping pattern.

20

36. A method for band spreading communications in a band
spreading communications system using orthogonal codes, the method

comprising the step of:

dividing the orthogonal codes into a first orthogonal code symbol group for code division multiplexing and a second orthogonal code symbol group for statistical multiplexing owing to orthogonal code hopping.

37. The method for band spreading communications as claimed in claim 36, further comprising the step of:

performing the code division multiplexing by fixedly allocating the orthogonal code symbols in the first orthogonal code symbol group to a channel having a high data activity in communications.

38. The method for band spreading communications as claimed in claim 36, further comprising the step of:

performing orthogonal code hopping multiplexing for a channel having a low data activity according to the orthogonal code hopping pattern by using only the orthogonal code symbols in the second orthogonal code symbol group.

39. The method for band spreading communications as claimed in claim 36,

wherein the orthogonal code is an orthogonal variable spreading

factor code.

40. The method for band spreading communications as claimed
in one of claims 36 to 39,

5 wherein the first orthogonal code symbol group consists of child
codes generated from one parent code in a hierarchical orthogonal code
generating tree structure according to the variable spreading factors;
and

10 wherein the second orthogonal code symbol group consists of
remained orthogonal code symbols.

41. The method for band spreading communications as claimed
in one of claims 36 to 39,

15 wherein the first orthogonal code symbol group used for the code
division multiplexing is selected to have a variable spreading gain
according to a send data rate.

42. The method for band spreading communications as claimed
in claim 40,

20 wherein the first orthogonal code symbol group used for the code
division multiplexing is selected to have a variable spreading gain
according to a send data rate.

43. The method for band spreading communications as claimed
in one of claims 36 to 39,

wherein the channel for the orthogonal code hopping multiplexing
5 has a fixed data rate,

the method further comprising the step of selecting orthogonal
code symbols having the same spreading factor in the second
orthogonal code symbol group.

10 44. The method for band spreading communications as claimed
in claim 40,

wherein the channel for the orthogonal code hopping multiplexing
has a fixed data rate,

the method further comprising the step of selecting orthogonal
15 code symbols having the same spreading factor in the second
orthogonal code symbol group.

ABSTRACT

Method and apparatus for statistically multiplexing corresponding channels using an orthogonal code hopping in a wire/wireless communication system in which a plurality of synchronized communication channels coexist through one media.

The system including a first communication station and a plurality of second communications includes an orthogonal code hopping pattern generator, a spreader for selecting a corresponding orthogonal code symbol in the orthogonal code, a collision comparator & controller for monitoring whether the orthogonal code symbols collide and determining whether the send data symbols to the second communication stations coincide in the collision area, a unit for stopping transmission in case of collision of the hopping patterns and discordance of the transmission data symbols, and a transmission power controller for compensating an average receiving energy loss.

FIG. 10a

10/030190

1/26

10030190 0670007




FIG. 1




FIG. 2a




FIG. 2b

4/26




FIG. 3a




FIG. 3b

6/26




FIG. 3c

7/26




FIG. 4a




FIG. 4b




FIG. 4c

FIG. 5




FIG. 6

11/26




FIG. 7

12/26




FIG. 8

13/26




FIG. 9

14/26




FIG. 10a




FIG. 10b




FIG. 10c




FIG. 11

18/26




FIG. 12

19/26




FIG. 13

20/26




FIG. 14a




FIG. 14b

21/26




FIG. 14c




FIG. 14d

10030190.020402

23/26




FIG. 14e

20140220 "06T0E00T

24/26




FIG. 14f

204020" 0510E00F

25/26




FIG. 14g

26/26




FIG. 14h




FIG. 15

Declaration and Power of Attorney For Utility or Design Patent Application English Language Declaration

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled

METHOD AND APPARATUS FOR ORTHOGONAL CODE HOPPING MULTIPLEXING COMMUNICATIONS

the specification of which is attached hereto unless the following box is checked:

was filed on _____ as

United States Application Number _____
and was amended on _____ (if applicable) or,

PCT International Application Number _____
and was amended on _____ (if applicable)

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, §1.56.

I hereby claim foreign priority benefits under Title 35, United States Code §119 (a-d) or §365(b) of any foreign application(s) for patent or inventor's certificate, or §365(a) of any PCT international application which designated at least one country other than the United States of America, listed below. I have also identified below, by checking the ANo box, any foreign application for patent or inventors certificate, or of any PCT international application having a filing date before that of the application on which priority is claimed:

			Priority Claimed	
(Number)	(Country)	(Day/Month/Year Filed)	Yes	No
1999-32187	Korea	05/08/1999	X	
(Number)	(Country)	(Day/Month/Year Filed)	Yes	No
(Number)	(Country)	(Day/Month/Year Filed)	Yes	No

Additional foreign application numbers are listed on a supplemental priority sheet attached hereto.

I hereby claim the benefit under Title 35, United States Code §119(e) of any United States provisional application(s) listed below.

(Number)	(Day/Month/Year Filed)
(Number)	(Day/Month/Year Filed)
(Number)	(Day/Month/Year Filed)

Additional provisional application numbers are listed on a supplemental priority sheet attached hereto.

204022" 06T0200T

I hereby claim the benefit under Title 35, United States Code §120 of any United States application(s), or §365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT international application in the manner provided by the first paragraph of Title 35, United States Code §112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations §1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application.

(Application No.)	(Filing Date)	(Status)
		(patented, pending, abandoned)

(Application No.)	(Filing Date)	(Status)
		(patented, pending, abandoned)

Additional U.S. or international application numbers are listed on a supplemental priority sheet attached hereto.

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

The undersigned hereby authorizes the U.S. attorney or agent named herein to accept and follow instructions from either his foreign patent agent or corporate representative, if any, as to any action to be taken in the Patent and Trademark Office regarding this application without direct communication between the U.S. attorney or agent and the undersigned. In the event of a change in the persons from whom instructions may be taken, the U.S. attorney or agent named herein will be so notified by the undersigned.

POWER OF ATTORNEY: As a named inventor, I hereby appoint the attorney(s) and/or agent(s) associated with the Customer Number provided below to prosecute this application and transact all business in the Patent and Trademark Office connected therewith, and direct that all correspondence be addressed to that Customer Number:

CUSTOMER NUMBER 7055

The appointed attorneys include:

Neil F. Greenblum	Reg. No. 28,394	Stephen M. Roylance	Reg. No. 31,296
Bruce H. Bernstein	Reg. No. 29,027	Leslie J. Paperner	Reg. No. 33,329
Arnold Turk	Reg. No. 33,094	William Pieprz	Reg. No. 33,630
James L. Rowland	Reg. No. 32,674	William E. Lyddane	Reg. No. 41,568

At: Greenblum & Bernstein, P.L.C.
1941 Roland Clarke Place
Reston, VA 20191

Direct Telephone Calls to: Greenblum & Bernstein, P.L.C. (703) 716-1191

Full name of sole or first inventor

SUNG, Dan-Keun

Inventor signature

[Signature]

Date
January 21, 2002

Address

Hanwool APT. 1503-103, Shisung-Dong, Yusong-Gu, Taejon, 305-035, Republic of Korea

KRX

Citizenship

Korea

(Supply similar information and signature for second and subsequent joint inventors.)

200	Full name of second joint inventor, if any <u>PARK, Su Won</u>	<i>Park Su Won</i>
	Second Inventor signature	Date January 20, 2002
	Address #373-1, Kusong-Dong, Yusong-Gu, <u>Taejeon</u> , 305-701, Republic of Korea <i>KRX</i>	
	Citizenship Korea	

20100202 06103001